

## Paging Power Amplifier

Add More Power to Your Existing Paging System



The M15W is designed to add more paging power to almost any amplified paging product, or it may be used as a primary paging amplifier. >BR> Audio can be input from a 600 ohm source or from an 8-ohm amplified source. The 15 watt output can drive an eight to four ohm load, or two separate two-ohm loads, which simplifies installation of up to eight 8-ohm speakers. A

- Applications:**
- Amplified loud Paging
  - Night bell
  - Loud ringing

**Model:** SH-609

**Part #:** Viking M15W

### Features

- Paging volume control
- Tone control
- 600 ohm input
- 8 ohm input
- 15 watts of paging power

### Specifications

Power: 120V AC/13.8 VAC 1.25A, UL listed adapter provided  
 Dimensions: 133mm x 89mm x 44mm (5.25" x 3.5" x 1.75")  
 Shipping Weight: 1.0 kg (2.2 lbs)  
 Environmental: 0° C to 32° C (32° F to 90° F) with 5% to 95% non-condensing humidity  
 Paging Output: 15 watts - powers up to (8) 8-ohm speakers  
 Frequency Response: 100 - 10K Hz  
 Sound Pressure: 118 db @ 1 meter  
 Speakers: (1) 25AE 8-ohm paging horn included, (8) maximum  
 Maximum Speaker Run: 91m (300 ft) maximum 18 AWG  
 Connections: 8 position screw terminal block