

## Series Weatherproof Proximity Reader



**Model:** SH-569

**Part #:** Hundure PXR -52E

### Features

- Compact and advanced design.
- Quick response, low interference, low power consumption and highly stable.
- Reading range up to 15cm without interference
- Interface ABA T2, Wiegand 26 bit, RS-485
- Weather proof Suitable to use in all places.
- Provide LED & Buzzer control input and can fir all controllers.
- The Case sensor provide the controller to guard against remove when destroy by violence the warning message will be show.

### Specifications

Communication interface:....  
 T2-ABA Track 2 W=Wiegand 485=RS-485  
 Input device: 1 Case sensor  
 Frequency: 125KHz  
 Indicators 1 dual color LED (Power/Status)  
 Beep tone: Buzzer  
 Operating voltage: DC12V@200mA  
 Power consumption: 1.5W (max)  
 Temperature: -10°C – 55°C / 14F -131F  
 Humidity: 20%-95% (non-condensing)

### Dimensions

Size: 76W x 120L x 23H (mm)  
 Weight: 130g

- Applications:**
- Apartment buildings and Condominiums
  - Senior citizen buildings
  - Assisted care centers
  - Retirement homes
  - Gated communities