

## Series Proximity Reader



**Model:** SH-572

**Part #:** Hundure PXR -62E

### Features

- Proximity card reader, can read EM card number.
- Interface: ABA T2, Wiegand 26 bit, RS-485.
- Weather proof, can install in-door and out-door, can fit all situations.
- Provide sound signal and can adjust the sound by efficient situation.
- The case sensor provide the controller to guard against remove, when destroy by violence, the warning message will be show.
- Quick response, low interference, low power consumption and highly stable.
- Reading range up to 15cm without interference.

### Specifications

Input device .... 1 (Case sensor)  
 Frequency : 125Khz  
 Reading range: 15cm (max)  
 Indicators : 1 pair of dual color LED (Power / Status)  
 Beep tone: Buzzer  
 Operating voltage: DC 12V@200mA  
 Power consumption: 1.5W (max)  
 Temperature: -10degC – 55degC / 14F -131F  
 Humidity: 20% - 95% (non-condensing)

### Dimensions

Size: 76Wx120Lx23H (mm)  
 Weight: 130g

- Applications:**
- Apartment buildings and Condominiums
  - Senior citizen buildings
  - Assisted care centers
  - Retirement homes
  - Gated communities