

Digital Home Theater Receiver – 7.1 Channel

Provides Handsfree Speakerphone, 3-Line Display and 24-Line Keys.



Model: SH-614

Part #: Yamaha RXV2500

Features

- Accurate Touch Volume Control
- 192 kHz/24-Bit DACs for All Channels
- Audio Delay for Adjusting Lip-Sync (0–240 ms)
- Analog Mixdown
- 2-Channel Stereo Mode and Straight/Effect Switch
- Digital Tone Controls for Front, Center, Presence and Subwoofer
- Rec Out/Zone 2 Selector
- Main/Zone 2 Direct On/Off Switch
- Zone 2 S-Video Output Terminal
- 9-Channel Speaker Outputs with Zone 2 Out
- Dialogue Lift for Enhanced Dialogue Sound
- Selectable 9-Band Subwoofer Crossover
- Subwoofer Phase Select
- Speaker A, B or A+B Selection (Front L/R)
- Night Listening Enhancer ensures that all programs (including Dolby Pro Logic IIx)
- SILENT CINEMA and Virtual CINEMA DSP
- Direct-Access (Macro-Command, Learning and Preset Capable) Remote Control Unit with Macro-Command Buttons and Illuminated Buttons

High sound quality, superior performance and surround realism are the result of the advanced technology that is part of the RX-V2500 digital home theater receiver.

Major features include 7-channel discrete amplification (130W x 7), Digital ToP-ART design concept, YPAO, Quad-Field CINEMA DSP, 19 surround programs, full movie sound format compatibility as well as THX Select processing, SILENT CINEMA, Night Listening Mode, 9 channel speaker outputs with Zone2 out, and component video up conversion for optimum video quality.

Features for convenient operation include extensive menus, front panel video Aux optical input terminal and a direct access remote control. This top-class receiver also provides a variety of features for setting up a multi-room custom installation.

- Applications:**
- Home Theater in Luxury Villa
 - Home Cinema Experience
 - Room sound optimization in Luxury Offices
 - Surround sound efficiency in Grand Hotels, Cineplex Cinemas